

**Amendment-I dated 29.05.2020 on the Request for Proposal and Transmission Service Agreement issued for selection of bidder as Transmission Service Provider to establish “Transmission system strengthening scheme for evacuation of power from solar energy zones in Rajasthan (8.1 GW) under Phase II -Part A” through tariff based competitive bidding process**

Sl. No.	Existing Clause	New / Revised Clause																				
1.	<p><b><u>SPECIFIC TECHNICAL REQUIREMENTS FOR TRANSMISSION LINE</u></b></p> <p>.....</p> <p>2.1. Steel section of grade E 250 and/or grade E 350 as per IS 2062, <b><u>are only</u></b> permitted for use in towers, extensions, gantry structures and stub setting templates. For towers in snowbound areas, steel sections shall conform to Grade-C of IS-2062</p> <p>.....</p> <p>6.0 The relevant conductor configuration shall be as follows:-</p> <p>i) Type of HTLS conductor: <b><u>INVAR/ GAP/ Composite core/ ACSS</u></b></p> <p>ii) Basic parameters:</p> <table border="1" data-bbox="257 1029 1160 1372"> <thead> <tr> <th>Transmissi on Line</th> <th>Ampacity of HTLS conductor</th> <th>Minimum Conductor diameter (mm)</th> <th>Maximum DC Resistance at 20°C (Ω/km)</th> <th>Sub-conductor Spacing (mm)</th> </tr> </thead> <tbody> <tr> <td><b><u>400kV</u></b> <b><u>(Twin HTLS)</u></b></td> <td>1596 A</td> <td>28.62</td> <td>0.05552</td> <td>450 mm</td> </tr> </tbody> </table>	Transmissi on Line	Ampacity of HTLS conductor	Minimum Conductor diameter (mm)	Maximum DC Resistance at 20°C (Ω/km)	Sub-conductor Spacing (mm)	<b><u>400kV</u></b> <b><u>(Twin HTLS)</u></b>	1596 A	28.62	0.05552	450 mm	<p><b><u>SPECIFIC TECHNICAL REQUIREMENTS FOR TRANSMISSION LINE</u></b></p> <p>.....</p> <p>2.1. Steel section of grade E 250 and/or grade E 350 as per IS 2062, <b><u>only are</u></b> permitted for use in towers, extensions, gantry structures and stub setting templates. For towers in snowbound areas, steel sections shall conform to Grade-C of IS-2062</p> <p>.....</p> <p>6.0 The relevant conductor configuration shall be as follows:-</p> <p>i) Type of conductor: <b><u>HTLS</u></b></p> <p>ii) Basic parameters:</p> <table border="1" data-bbox="1191 1029 2094 1372"> <thead> <tr> <th>Transmissi on Line</th> <th>Ampacity of HTLS conductor (for ambient temperature of 45°C)</th> <th>Minimum Conductor diameter (mm)</th> <th>Maximum DC Resistance at 20°C (Ω/km)</th> <th>Sub-conductor Spacing (mm)</th> </tr> </thead> <tbody> <tr> <td><b><u>400kV transmissi</u></b></td> <td>1596 A</td> <td>28.62</td> <td>0.05552</td> <td>450</td> </tr> </tbody> </table>	Transmissi on Line	Ampacity of HTLS conductor (for ambient temperature of 45°C)	Minimum Conductor diameter (mm)	Maximum DC Resistance at 20°C (Ω/km)	Sub-conductor Spacing (mm)	<b><u>400kV transmissi</u></b>	1596 A	28.62	0.05552	450
Transmissi on Line	Ampacity of HTLS conductor	Minimum Conductor diameter (mm)	Maximum DC Resistance at 20°C (Ω/km)	Sub-conductor Spacing (mm)																		
<b><u>400kV</u></b> <b><u>(Twin HTLS)</u></b>	1596 A	28.62	0.05552	450 mm																		
Transmissi on Line	Ampacity of HTLS conductor (for ambient temperature of 45°C)	Minimum Conductor diameter (mm)	Maximum DC Resistance at 20°C (Ω/km)	Sub-conductor Spacing (mm)																		
<b><u>400kV transmissi</u></b>	1596 A	28.62	0.05552	450																		

Sl. No.	Existing Clause					New / Revised Clause										
	<u>transmissi on line</u>					<u>on line with Twin HTLS conductor</u>										
	<p>.....</p> <p>8.0 All electrical clearances including minimum live metal clearance, ground clearance and minimum mid span separation between earth wire and conductor shall be as per Central Electricity Authority (Measures Relating to Safety &amp; Electric Supply) Regulations as amended from time to time and IS:5613.</p> <p>.....</p> <p>12.0 Each tower shall be earthed such that tower footing impedance does not exceed 10 ohms. Pipe type or Counterpoise type earthing shall be provided in accordance with relevant IS. Additional earthing</p>					<p>.....</p> <p>8.0 All electrical clearances including minimum live metal clearance, ground clearance and minimum mid span separation between earth wire and conductor shall be as per Central Electricity Authority (Measures Relating to Safety &amp; Electric Supply) Regulations as amended from time to time and IS:5613.</p> <p>a) <b><u>The minimum live metal clearances for 400 kV D/C transmission lines shall be considered as follows:</u></b></p> <p>(i) <b><u>Under stationary conditions</u></b></p> <p style="padding-left: 40px;"><b><u>From tower body: 3.05m</u></b></p> <p>(ii) <b><u>Under Swing conditions</u></b></p> <table border="1" data-bbox="1335 1002 2085 1209"> <thead> <tr> <th><u>Wind Pressure Condition</u></th> <th><u>Minimum Electrical Clearance</u></th> </tr> </thead> <tbody> <tr> <td>a) <u>Swing angle (22°)</u></td> <td><b>3.05 mtrs</b></td> </tr> <tr> <td>b) <u>Swing angle (44°)</u></td> <td><b>1.86 mtrs</b></td> </tr> </tbody> </table> <p>.....</p> <p>12.0 Each tower shall be earthed such that tower footing impedance does not exceed 10 ohms. Pipe type or Counterpoise type earthing shall be provided in accordance with relevant IS. Additional earthing</p>					<u>Wind Pressure Condition</u>	<u>Minimum Electrical Clearance</u>	a) <u>Swing angle (22°)</u>	<b>3.05 mtrs</b>	b) <u>Swing angle (44°)</u>	<b>1.86 mtrs</b>
<u>Wind Pressure Condition</u>	<u>Minimum Electrical Clearance</u>															
a) <u>Swing angle (22°)</u>	<b>3.05 mtrs</b>															
b) <u>Swing angle (44°)</u>	<b>1.86 mtrs</b>															

Sl. No.	Existing Clause	New / Revised Clause
	<p>shall be provided on every 7 to 8 kms distance at tension tower for direct earthing of both shield wires.</p>	<p>shall be provided on every 7 to 8 kms distance at tension tower for direct earthing of both shield wires. <b><u>If site condition demands, multiple earthing or use of earthing enhancement compound shall be used.</u></b></p> <p><b><u>13.0 The transmission lines shall be designed with porcelain disc insulators or porcelain long rod insulators with the specific creepage distance required as per Site Pollution Severity level in the concerned area provided that the specific creepage distance shall not be less than 25 mm/kV.</u></b></p> <p><b><u>14.0 Pile foundation shall be used for towers located in the river bed, or on river banks or in areas where river flow or river course is anticipated to change based on previous years' hydrology data.</u></b></p> <p><b><u>15.0 Transmission line route shall be finalized, in consultation with appropriate authorities so as to avoid the habitant zones of Great Indian Bustard and other protected species. Bird diverters, wherever required, shall be provided on the line.</u></b></p>
2.	<p><b><u>SPECIFIC TECHNICAL REQUIREMENTS FOR SUBSTATION</u></b></p> <p>The proposed new substation shall be conventional AIS type generally conforming to the requirement of <b><u>CEA regulation for construction of substation.</u></b></p> <p>The proposed augmentation at Fatehgarh-II S/s shall be AIS type generally conforming to the requirement of <b><u>CEA regulation for construction of substation.</u></b></p>	<p><b><u>SPECIFIC TECHNICAL REQUIREMENTS FOR SUBSTATION</u></b></p> <p>The proposed new substation shall be conventional AIS type generally conforming to the requirement of <b><u>CEA (Technical Standards for Construction of Electrical Plants and Electric Lines) Regulations 2010, as amended from time to time.</u></b></p> <p>The proposed augmentation at Fatehgarh-II S/s shall be AIS type generally conforming to the requirement of <b><u>CEA (Technical Standards for Construction of Electrical Plants and Electric Lines) Regulations 2010, as amended from time to time.</u></b></p>

Sl. No.	Existing Clause						New / Revised Clause																																																					
	<p>The proposed augmentation at Jaisalmer-II (RVPN) S/s shall be AIS type generally conforming to the requirement of <b><u>CEA regulation for construction of substation</u></b> (to be confirmed by RVPN).</p>						<p>The proposed augmentation at Jaisalmer-II (RVPN) S/s shall be AIS type generally conforming to the requirement of <b><u>CEA (Technical Standards for Construction of Electrical Plants and Electric Lines) Regulations 2010, as amended from time to time.</u></b></p>																																																					
	<p><b>1.1. Insulation Coordination</b> The system design parameters for substations/switchyards shall be as given below:</p>						<p><b>1.1. Insulation Coordination</b> The system design parameters for substations/switchyards shall be as given below:</p>																																																					
	<table border="1" data-bbox="264 539 1160 1026"> <thead> <tr> <th data-bbox="264 539 338 818">Sl. No</th> <th data-bbox="338 539 607 818">Description of parameters</th> <th colspan="2" data-bbox="607 539 875 730">400/220kV Ramgarh-II PS</th> <th data-bbox="875 539 1025 730">400kV Fatehgarh-II PS Extn.</th> <th data-bbox="1025 539 1160 730">400kV Jaisalmer-II (RVPN) Extn.</th> </tr> <tr> <td></td> <td></td> <th data-bbox="607 730 745 818">400 kV System</th> <th data-bbox="745 730 875 818">220 kV System</th> <th data-bbox="875 730 1025 818">400 kV System</th> <th data-bbox="1025 730 1160 818">400 kV System</th> </tr> </thead> <tbody> <tr> <td data-bbox="264 818 338 874">...</td> <td data-bbox="338 818 607 874">...</td> <td data-bbox="607 818 745 874">...</td> <td data-bbox="745 818 875 874">...</td> <td data-bbox="875 818 1025 874">...</td> <td data-bbox="1025 818 1160 874">...</td> </tr> <tr> <td data-bbox="264 874 338 1026">10.</td> <td data-bbox="338 874 607 1026">Max. fault current</td> <td data-bbox="607 874 745 1026">63kA</td> <td data-bbox="745 874 875 1026">50kA</td> <td data-bbox="875 874 1025 1026">50kA</td> <td data-bbox="1025 874 1160 1026"><u>BPC to obtain from RVPN</u></td> </tr> </tbody> </table>						Sl. No	Description of parameters	400/220kV Ramgarh-II PS		400kV Fatehgarh-II PS Extn.	400kV Jaisalmer-II (RVPN) Extn.			400 kV System	220 kV System	400 kV System	400 kV System	...	...	...	...	...	...	10.	Max. fault current	63kA	50kA	50kA	<u>BPC to obtain from RVPN</u>	<table border="1" data-bbox="1198 523 2078 914"> <thead> <tr> <th data-bbox="1198 523 1272 802">Sl. No</th> <th data-bbox="1272 523 1541 802">Description of parameters</th> <th colspan="2" data-bbox="1541 523 1809 707">400/220kV Ramgarh-II PS</th> <th data-bbox="1809 523 1955 707">400kV Fatehgarh-II PS Extn.</th> <th data-bbox="1955 523 2078 707">400kV Jaisalmer-II (RVPN) Extn.</th> </tr> <tr> <td></td> <td></td> <th data-bbox="1541 707 1675 802">400 kV System</th> <th data-bbox="1675 707 1809 802">220 kV System</th> <th data-bbox="1809 707 1955 802">400 kV System</th> <th data-bbox="1955 707 2078 802">400 kV System</th> </tr> </thead> <tbody> <tr> <td data-bbox="1198 802 1272 858">...</td> <td data-bbox="1272 802 1541 858">...</td> <td data-bbox="1541 802 1675 858">...</td> <td data-bbox="1675 802 1809 858">...</td> <td data-bbox="1809 802 1955 858">...</td> <td data-bbox="1955 802 2078 858">...</td> </tr> <tr> <td data-bbox="1198 858 1272 914">10.</td> <td data-bbox="1272 858 1541 914">Max. fault current</td> <td data-bbox="1541 858 1675 914">63kA</td> <td data-bbox="1675 858 1809 914">50kA</td> <td data-bbox="1809 858 1955 914">50kA</td> <td data-bbox="1955 858 2078 914"><u>63kA</u></td> </tr> </tbody> </table>						Sl. No	Description of parameters	400/220kV Ramgarh-II PS		400kV Fatehgarh-II PS Extn.	400kV Jaisalmer-II (RVPN) Extn.			400 kV System	220 kV System	400 kV System	400 kV System	...	...	...	...	...	...	10.	Max. fault current	63kA	50kA	50kA	<u>63kA</u>
Sl. No	Description of parameters	400/220kV Ramgarh-II PS		400kV Fatehgarh-II PS Extn.	400kV Jaisalmer-II (RVPN) Extn.																																																							
		400 kV System	220 kV System	400 kV System	400 kV System																																																							
...	...	...	...	...	...																																																							
10.	Max. fault current	63kA	50kA	50kA	<u>BPC to obtain from RVPN</u>																																																							
Sl. No	Description of parameters	400/220kV Ramgarh-II PS		400kV Fatehgarh-II PS Extn.	400kV Jaisalmer-II (RVPN) Extn.																																																							
		400 kV System	220 kV System	400 kV System	400 kV System																																																							
...	...	...	...	...	...																																																							
10.	Max. fault current	63kA	50kA	50kA	<u>63kA</u>																																																							
	<p><b>1.2. Switching Scheme</b> The switching schemes, as mentioned below, shall be adopted at various voltage levels of substation/switchyard: ... i. At 400kV voltage level, each circuit of a double circuit transmission line shall be terminated in different diameters. ii. Transformers of same HV rating shall be placed in different diameters.</p>						<p><b>1.2. Switching Scheme</b> The switching schemes, as mentioned below, shall be adopted at various voltage levels of substation/switchyard: ... i. At 400kV voltage level, each circuit of a double circuit transmission line shall be terminated in different diameters.</p>																																																					

Sl. No.	Existing Clause						New / Revised Clause																																																																									
	<p><b>2.0 Substation Equipment and facilities:</b> The switchgear shall be designed and specified to withstand operating conditions and duty requirements. All equipment shall be designed considering the transmission line capacity.</p> <table border="1" data-bbox="264 571 1160 1018"> <thead> <tr> <th rowspan="2">Sl. No</th> <th rowspan="2">Description of bay</th> <th colspan="2">400/220kV Ramgarh-II PS</th> <th>400kV Fatehgarh-II Extn.</th> <th>400 Jaisalmer-II Extn.</th> </tr> <tr> <th>400 kV</th> <th>220 kV</th> <th>400 kV</th> <th>400 kV</th> </tr> </thead> <tbody> <tr> <td>1.</td> <td>Bus Bar</td> <td>4000A</td> <td><u>4000A</u></td> <td><u>4000A</u></td> <td><u>4000A</u></td> </tr> <tr> <td colspan="6">.....</td> </tr> <tr> <td>5</td> <td>Bus Coupler bay</td> <td>-</td> <td><u>4000A</u></td> <td>--</td> <td>-</td> </tr> <tr> <td colspan="6">.....</td> </tr> </tbody> </table> <p><b><u>However, current rating of all equipment in one diameter shall be the highest current rating required for connected line/ICT so that the system could operate without any constraint in case of outage of any bus bar.</u></b></p> <p>.....</p> <p><b>2.1. 400/220kV, 3-Phase Transformer</b></p>						Sl. No	Description of bay	400/220kV Ramgarh-II PS		400kV Fatehgarh-II Extn.	400 Jaisalmer-II Extn.	400 kV	220 kV	400 kV	400 kV	1.	Bus Bar	4000A	<u>4000A</u>	<u>4000A</u>	<u>4000A</u>	.....						5	Bus Coupler bay	-	<u>4000A</u>	--	-	.....						<p>ii. Transformers <b><u>and bus reactors</u></b> of same HV rating shall be placed in different diameters.</p> <p><b>2.0 Substation Equipment and facilities:</b> The switchgear shall be designed and specified to withstand operating conditions and duty requirements. All equipment shall be designed considering the transmission line capacity.</p> <table border="1" data-bbox="1198 571 2072 1018"> <thead> <tr> <th rowspan="2">Sl. No</th> <th rowspan="2">Description of bay</th> <th colspan="2">400/220kV Ramgarh-II PS</th> <th>400kV Fatehgarh-II Extn.</th> <th>400 Jaisalmer-II Extn.</th> </tr> <tr> <th>400 kV</th> <th>220 kV</th> <th>400 kV</th> <th>400 kV</th> </tr> </thead> <tbody> <tr> <td>1.</td> <td>Bus Bar</td> <td>4000A</td> <td><u>3150A</u></td> <td><b>Same as existing</b></td> <td><b>Same as existing</b></td> </tr> <tr> <td colspan="6">.....</td> </tr> <tr> <td>5.</td> <td>Bus Coupler bay</td> <td>-</td> <td><u>3150A</u></td> <td>--</td> <td>--</td> </tr> <tr> <td colspan="6">.....</td> </tr> </tbody> </table> <p>.....</p> <p><b>2.1. 400/220kV, 3-Phase Transformer</b></p>						Sl. No	Description of bay	400/220kV Ramgarh-II PS		400kV Fatehgarh-II Extn.	400 Jaisalmer-II Extn.	400 kV	220 kV	400 kV	400 kV	1.	Bus Bar	4000A	<u>3150A</u>	<b>Same as existing</b>	<b>Same as existing</b>	.....						5.	Bus Coupler bay	-	<u>3150A</u>	--	--	.....					
Sl. No	Description of bay	400/220kV Ramgarh-II PS		400kV Fatehgarh-II Extn.	400 Jaisalmer-II Extn.																																																																											
		400 kV	220 kV	400 kV	400 kV																																																																											
1.	Bus Bar	4000A	<u>4000A</u>	<u>4000A</u>	<u>4000A</u>																																																																											
.....																																																																																
5	Bus Coupler bay	-	<u>4000A</u>	--	-																																																																											
.....																																																																																
Sl. No	Description of bay	400/220kV Ramgarh-II PS		400kV Fatehgarh-II Extn.	400 Jaisalmer-II Extn.																																																																											
		400 kV	220 kV	400 kV	400 kV																																																																											
1.	Bus Bar	4000A	<u>3150A</u>	<b>Same as existing</b>	<b>Same as existing</b>																																																																											
.....																																																																																
5.	Bus Coupler bay	-	<u>3150A</u>	--	--																																																																											
.....																																																																																

Sl. No.	Existing Clause	New / Revised Clause
	<p>Transformer shall conform to IEC 60076 in general. The 500 MVA transformers shall be designed based on design of dynamic short circuit tested 315 MVA or 500 MVA transformers. The transformer and all its accessories including bushing/ built in CTs etc shall be designed to withstand thermal and mechanical stresses caused by symmetrical or asymmetrical faults on any terminals. Mechanical strength of the transformer shall be such that it can withstand 3-phase and 1- phase through fault for transformer rated voltage applied to HV and / or IV terminals of transformer. The short circuit shall alternatively be considered to be applied to each of the HV, IV and tertiary (LV) transformer terminals.</p> <p>....</p> <p>The transformer shall be complete with all required accessories, Bushing CTs, cooler control cabinet, individual and common marshalling box, <b><u>RTCC</u></b> etc as required for satisfactory operations of transformer. <b><u>The transformer shall be provided with IEC 61850 compliant digital RTCC relay having automatic voltage regulating features using Bay control and protection unit used for SAS, to operate OLTC including parallel operation of transformers.</u></b></p> <p>Neutral of the transformer shall be solidly grounded.</p> <p><b><u>HV, IV and LV bushing shall be RIP (resin impregnated paper condenser) with composite insulator type. 36kV Neutral bushing shall be solid porcelain or oil communicating type.</u></b></p>	<p>Transformer shall conform to IEC 60076 in general. The 500 MVA transformers shall be designed based on design of dynamic short circuit tested 315 MVA or 500 MVA transformers. The transformer and all its accessories including bushing/ built in CTs etc shall be designed to withstand thermal and mechanical stresses caused by symmetrical or asymmetrical faults on any terminals. Mechanical strength of the transformer shall be such that it can withstand 3-phase and 1- phase through fault for transformer rated voltage applied to HV and / or IV terminals of transformer. The short circuit shall alternatively be considered to be applied to each of the HV, IV and tertiary (LV) transformer terminals. <b><u>Tertiary is not considered to be connected to source. The maximum short circuit output current at the tertiary terminals shall be limited to a safe value to make the transformer short circuit proof. The Tertiary winding shall be designed to withstand mechanical and thermal stresses due to dead short circuit on its terminals. However, the cooling for continuous thermal rating of the tertiary winding shall be for at least 5 MVA capacity.</u></b></p> <p>....</p> <p>The transformer shall be complete with all required accessories, Bushing CTs, cooler control cabinet, individual and common marshalling box, etc. as required for satisfactory operations of transformer. <b><u>Remote tap changer control and monitoring system including parallel operation of transformer shall be carried out using Bay control unit or digital RTCC relay through Substation Automation System.</u></b></p> <p>Neutral of the transformer shall be solidly grounded.</p> <p><b><u>HV, and IV bushing shall be RIP (Resin Impregnated Paper) / RIS (Resin Impregnated Synthetic) with composite insulator type. LV</u></b></p>

Sl. No.	Existing Clause				New / Revised Clause																																			
	<p>The major technical particulars / parameters of transformer are given below:</p> <table border="1" data-bbox="259 331 1155 625"> <thead> <tr> <th colspan="4" data-bbox="259 331 1155 418">Technical Particulars / Parameters of 500MVA, 400/220/33kV, 3-Phase Autotransformer</th> </tr> <tr> <th data-bbox="259 418 349 475">Sl. No.</th> <th data-bbox="349 418 685 475">Description</th> <th data-bbox="685 418 792 475">Unit</th> <th data-bbox="792 418 1155 475">Technical Parameters</th> </tr> </thead> <tbody> <tr> <td data-bbox="259 475 349 533">..</td> <td data-bbox="349 475 685 533">...</td> <td data-bbox="685 475 792 533">...</td> <td data-bbox="792 475 1155 533">.....</td> </tr> <tr> <td data-bbox="259 533 349 625">15</td> <td data-bbox="349 533 685 625">Insulating Oil</td> <td data-bbox="685 533 792 625"></td> <td data-bbox="792 533 1155 625"><u>Virgin high grade</u> inhibited, conforming to IEC-60296</td> </tr> </tbody> </table> <p><b>2.2. 420kV, 3-Phase, Shunt Reactor</b></p> <p>...</p> <p>The reactor shall be of <u>either</u> gapped core type <u>or magnetically shielded air core type (shell type)</u> construction. The impedance ratio (X0/X1) specified shall be achieved by adopting either single phase construction in separate tanks or three phase with 3 limb or 5 limb core construction. <u>In case of coreless construction, a magnetic shield shall be provided around the coreless coils and non-magnetic material sheet shall form the central core to minimize the vibrations.</u> Core shall be constructed from non-ageing, cold rolled grain oriented silicon steel laminations with requisite BIS certification.</p> <p>....</p>				Technical Particulars / Parameters of 500MVA, 400/220/33kV, 3-Phase Autotransformer				Sl. No.	Description	Unit	Technical Parameters	..	...	...	.....	15	Insulating Oil		<u>Virgin high grade</u> inhibited, conforming to IEC-60296	<p><b><u>bushing shall be OIP/RIP/RIS. 36kV Neutral bushing shall be solid porcelain or oil communicating type.</u></b></p> <p>The major technical particulars / parameters of transformer are given below:</p> <table border="1" data-bbox="1191 427 2087 785"> <thead> <tr> <th colspan="4" data-bbox="1191 427 2087 513">Technical Particulars / Parameters of 500MVA, 400/220/33kV, 3-Phase Autotransformer</th> </tr> <tr> <th data-bbox="1191 513 1281 571">Sl. No.</th> <th data-bbox="1281 513 1617 571">Description</th> <th data-bbox="1617 513 1724 571">Unit</th> <th data-bbox="1724 513 2087 571">Technical Parameters</th> </tr> </thead> <tbody> <tr> <td data-bbox="1191 571 1281 628">..</td> <td data-bbox="1281 571 1617 628">...</td> <td data-bbox="1617 571 1724 628">...</td> <td data-bbox="1724 571 2087 628">.....</td> </tr> <tr> <td data-bbox="1191 628 1281 785">15</td> <td data-bbox="1281 628 1617 785">Insulating Oil</td> <td data-bbox="1617 628 1724 785"></td> <td data-bbox="1724 628 2087 785"><u>Unused</u> inhibited <u>or uninhibited transformer oil</u>, conforming to IEC-60296-2012</td> </tr> </tbody> </table> <p><b>2.2. 420kV, 3-Phase, Shunt Reactor</b></p> <p>...</p> <p>The reactor shall be of <u>gapped core type construction</u>. The impedance ratio (X0/X1) specified shall be achieved by adopting either single phase construction in separate tanks or three phase with 3 limb or 5 limb core construction. Core shall be constructed from non-ageing, cold rolled grain oriented silicon steel laminations with requisite BIS certification.</p> <p>.....</p>				Technical Particulars / Parameters of 500MVA, 400/220/33kV, 3-Phase Autotransformer				Sl. No.	Description	Unit	Technical Parameters	..	...	...	.....	15	Insulating Oil		<u>Unused</u> inhibited <u>or uninhibited transformer oil</u> , conforming to IEC-60296-2012
Technical Particulars / Parameters of 500MVA, 400/220/33kV, 3-Phase Autotransformer																																								
Sl. No.	Description	Unit	Technical Parameters																																					
..	...	...	.....																																					
15	Insulating Oil		<u>Virgin high grade</u> inhibited, conforming to IEC-60296																																					
Technical Particulars / Parameters of 500MVA, 400/220/33kV, 3-Phase Autotransformer																																								
Sl. No.	Description	Unit	Technical Parameters																																					
..	...	...	.....																																					
15	Insulating Oil		<u>Unused</u> inhibited <u>or uninhibited transformer oil</u> , conforming to IEC-60296-2012																																					

Sl. No.	Existing Clause	New / Revised Clause																																																																																
	<p>The reactor shall be complete with all required accessories, Bushing CTs, marshalling box etc as required for satisfactory operations of reactor. HV and Neutral bushings shall be RIP (<del>resin impregnated paper condenser</del>) with composite insulator type.</p> <p>The Technical Particulars / Parameters of Shunt Reactor are given below:</p> <table border="1" data-bbox="257 555 1160 1337"> <thead> <tr> <th>Sl. No.</th> <th>Description</th> <th>Unit</th> <th>Parameters</th> </tr> </thead> <tbody> <tr> <td>1.1</td> <td>Rated Voltage, Ur (1p.u)</td> <td>kV</td> <td>420</td> </tr> <tr> <td>1.2</td> <td>Rated Capacity at 420kV</td> <td>MVAR</td> <td>125</td> </tr> <tr> <td>1.3</td> <td>Cooling System</td> <td></td> <td>ONAN</td> </tr> <tr> <td>1.4</td> <td>Permissible current unbalance among different phases</td> <td>%</td> <td>±2</td> </tr> <tr> <td>1.5</td> <td>Crest value of Third Harmonic content in phase current at rated voltage with sinusoidal wave form</td> <td>%</td> <td>≤ 3% of the crest value of fundamental</td> </tr> <tr> <td>1.6</td> <td>Range of constant Impedance</td> <td></td> <td>Up to 1.5 p.u. voltage</td> </tr> <tr> <td>1.7</td> <td>Tolerance on current</td> <td>%</td> <td>0 to +5%</td> </tr> <tr> <td>1.8</td> <td>Ratio of zero sequence reactance to positive reactance (X0/X1)</td> <td>Range</td> <td>0.9 - 1.0.</td> </tr> </tbody> </table>	Sl. No.	Description	Unit	Parameters	1.1	Rated Voltage, Ur (1p.u)	kV	420	1.2	Rated Capacity at 420kV	MVAR	125	1.3	Cooling System		ONAN	1.4	Permissible current unbalance among different phases	%	±2	1.5	Crest value of Third Harmonic content in phase current at rated voltage with sinusoidal wave form	%	≤ 3% of the crest value of fundamental	1.6	Range of constant Impedance		Up to 1.5 p.u. voltage	1.7	Tolerance on current	%	0 to +5%	1.8	Ratio of zero sequence reactance to positive reactance (X0/X1)	Range	0.9 - 1.0.	<p>The reactor shall be complete with all required accessories, Bushing CTs, marshalling box etc as required for satisfactory operations of reactor. HV and Neutral bushings shall be RIP (<del>Resin Impregnated Paper</del>)/<b><u>RIS (Resin Impregnated Synthetic)</u></b> with composite insulator type.</p> <p>The Technical Particulars / Parameters of <b><u>3-phase, 125 MVar, 420 kV</u></b> Shunt Reactor are given below:</p> <table border="1" data-bbox="1191 592 2085 1345"> <thead> <tr> <th>Sl. No.</th> <th>Description</th> <th>Unit</th> <th>Technical Parameters</th> </tr> </thead> <tbody> <tr> <td>1.</td> <td>Rated Capacity at 420kV</td> <td>MVar</td> <td><b>125</b></td> </tr> <tr> <td>2.</td> <td>Rated Voltage (Ur) (1.0 pu)</td> <td>kV</td> <td>420</td> </tr> <tr> <td>3.</td> <td><b><u>Number of phases</u></b></td> <td></td> <td><b><u>3 (three)</u></b></td> </tr> <tr> <td>4.</td> <td><b><u>Connection</u></b></td> <td></td> <td><b><u>Star</u></b></td> </tr> <tr> <td>5.</td> <td>Cooling type</td> <td></td> <td>ONAN</td> </tr> <tr> <td>6.</td> <td><b><u>Frequency</u></b></td> <td><b><u>Hz</u></b></td> <td><b><u>50</u></b></td> </tr> <tr> <td>7.</td> <td><b><u>Reference standard</u></b></td> <td></td> <td><b><u>IEC 60076-6</u></b></td> </tr> <tr> <td>8.</td> <td><b><u>Service</u></b></td> <td></td> <td><b><u>Outdoor</u></b></td> </tr> <tr> <td>9.</td> <td>Permissible unbalance current among phases</td> <td>%</td> <td>±2%</td> </tr> <tr> <td>10.</td> <td>Crest value of third harmonic content in phase current at rated voltage with sinusoidal wave form</td> <td>%</td> <td>≤ 3% of the crest value of fundamental</td> </tr> </tbody> </table>	Sl. No.	Description	Unit	Technical Parameters	1.	Rated Capacity at 420kV	MVar	<b>125</b>	2.	Rated Voltage (Ur) (1.0 pu)	kV	420	3.	<b><u>Number of phases</u></b>		<b><u>3 (three)</u></b>	4.	<b><u>Connection</u></b>		<b><u>Star</u></b>	5.	Cooling type		ONAN	6.	<b><u>Frequency</u></b>	<b><u>Hz</u></b>	<b><u>50</u></b>	7.	<b><u>Reference standard</u></b>		<b><u>IEC 60076-6</u></b>	8.	<b><u>Service</u></b>		<b><u>Outdoor</u></b>	9.	Permissible unbalance current among phases	%	±2%	10.	Crest value of third harmonic content in phase current at rated voltage with sinusoidal wave form	%	≤ 3% of the crest value of fundamental
Sl. No.	Description	Unit	Parameters																																																																															
1.1	Rated Voltage, Ur (1p.u)	kV	420																																																																															
1.2	Rated Capacity at 420kV	MVAR	125																																																																															
1.3	Cooling System		ONAN																																																																															
1.4	Permissible current unbalance among different phases	%	±2																																																																															
1.5	Crest value of Third Harmonic content in phase current at rated voltage with sinusoidal wave form	%	≤ 3% of the crest value of fundamental																																																																															
1.6	Range of constant Impedance		Up to 1.5 p.u. voltage																																																																															
1.7	Tolerance on current	%	0 to +5%																																																																															
1.8	Ratio of zero sequence reactance to positive reactance (X0/X1)	Range	0.9 - 1.0.																																																																															
Sl. No.	Description	Unit	Technical Parameters																																																																															
1.	Rated Capacity at 420kV	MVar	<b>125</b>																																																																															
2.	Rated Voltage (Ur) (1.0 pu)	kV	420																																																																															
3.	<b><u>Number of phases</u></b>		<b><u>3 (three)</u></b>																																																																															
4.	<b><u>Connection</u></b>		<b><u>Star</u></b>																																																																															
5.	Cooling type		ONAN																																																																															
6.	<b><u>Frequency</u></b>	<b><u>Hz</u></b>	<b><u>50</u></b>																																																																															
7.	<b><u>Reference standard</u></b>		<b><u>IEC 60076-6</u></b>																																																																															
8.	<b><u>Service</u></b>		<b><u>Outdoor</u></b>																																																																															
9.	Permissible unbalance current among phases	%	±2%																																																																															
10.	Crest value of third harmonic content in phase current at rated voltage with sinusoidal wave form	%	≤ 3% of the crest value of fundamental																																																																															

Sl. No.	Existing Clause			New / Revised Clause				
	1.9	Max. Temperature rise over 50 deg C Ambient Temp. at rated voltage	Deg. C	Top oil: 40 & Winding:45	11.	Range of constant impedance		Up to 1.5 p.u voltage (However, complete saturation characteristics of the Reactors upto 2.5 p.u. Voltage shall be furnished)
	1.10	(a) Maximum Permissible load Losses at rated Voltage, Frequency and at 75° C (kW) for 420kV, 125 MVAR, 3-Phase Reactor	kW	160	12.	Tolerance on current	%	0 to +5%
		(b) Maximum Permissible I <sup>2</sup> R Losses of Reactor at rated Voltage, Frequency and at 75°	kW	90	13.	Ratio of zero sequence reactance to positive reactance (X <sub>0</sub> /X <sub>1</sub> )		Between 0.9 & 1.0.
	1.11	Windings			14.	Temperature rise over 50 °C Ambient Temp. at 420 kV		
	a)	Insulation level (LI/SI/PF)		kVp/ kVp/kVrms	i)	<u>Top oil measured by thermometer</u>	°C	<u>40</u>
		HV		1300/1050/-	ii)	<u>Average winding measured by resistance method</u>	°C	<u>45</u>
		Neutral		550/-/230	15.	<u>Winding hot spot temperature rise over yearly weighted average temperature of 32 °C</u>	°C	<u>61</u>
	b)	Tan delta of windings	%	< 0.5	16.	<u>Max. tank surface temperature</u>	°C	<u>110</u>
	1.11	Partial discharge (PD) level at 1.58 Ur/√3	pC	<100	17.	<u>Max design ambient temperature</u>	°C	<u>50</u>
	1.12	Vibration & Tank stress level at rated voltage and frequency		≤ 200 microns peak to peak; Average: ≤60 microns peak to peak.  Stress: ≤ 2.0kg/sq.mm at any point on tank.	18.	Windings		

Sl. No.	Existing Clause			New / Revised Clause				
	1.13	Noise level at rated voltage and frequency	dB	< 80	i)	<u>Lightning Impulse withstand Voltage</u>		
	1.14	Bushing				<u>Line end</u>	<u>kV<sub>p</sub></u>	<u>1300</u>
	a)	Rated voltage : HV / Neutral	kV	420/145		<u>Neutral</u>	<u>kV<sub>p</sub></u>	<u>550</u>
	b)	Rated current (Min.) HV / Neutral	A	800/800	ii)	<u>Chopped Wave Lightning Impulse Withstand Voltage</u>		
	c)	Insulation level (LI/SI/PF)		kVp/ kVp / kVrms		<u>Line end</u>	<u>kV<sub>p</sub></u>	<u>1430</u>
		HV		1425/1050/695	iii)	<u>Switching Impulse withstand Voltage at Line end</u>	<u>kV<sub>p</sub></u>	<u>1050</u>
		Neutral		650/-/305	iv)	<u>One Minute Power Frequency withstand Voltage</u>		
	d)	Tan delta of bushings : HV /Neutral	%	< 0.5		<u>Neutral</u>	<u>kVrms</u>	<u>230</u>
	e)	PD of bushings at level Um	pC	<10	19.	Tan-delta of windings		< 0.005
	1.15	Insulating Oil		<u>Virgin high grade</u> inhibited, conforming to IEC-60296	20.	<u>Neutral earthing</u>		<u>Solidly Earthed</u>
					21.	<u>Whether neutral brought out</u>		<u>Yes (through 145kV class bushing)</u>
					22.	<u>Bushing</u>		
					i)	<u>Rated voltage</u>		
						<u>Line bushing</u>	<u>kV</u>	<u>420</u>
						<u>Neutral bushing</u>	<u>kV</u>	<u>145</u>

Sl. No.	Existing Clause	New / Revised Clause			
		ii)	<b>Rated current</b>		
			<b>Line bushing</b>	<b>A</b> <b>800</b>	
			<b>Neutral bushing</b>	<b>A</b> <b>800</b>	
		iii)	<b>Lightning Impulse withstand Voltage</b>		
			<b>Line bushing</b>	<b>kV<sub>p</sub></b> <b>1425</b>	
			<b>Neutral bushing</b>	<b>kV<sub>p</sub></b> <b>650</b>	
		iv)	<b>Switching Impulse withstand Voltage of Line bushing</b>	<b>kV<sub>p</sub></b> <b>1050</b>	
		v)	<b>1minute power frequency withstand of bushings (dry)</b>		
			<b>Line bushing</b>	<b>kV rms</b> <b>695</b>	
			<b>Neutral bushing</b>	<b>kV rms</b> <b>305</b>	
		vi)	<b>Minimum creepage distance</b>		<b>(Specific Creepage Distance: of 25mm/kV corresponding to highest line to line voltage)</b>
			<b>Line bushing</b>	<b>mm</b> <b>10500</b>	
			<b>Neutral bushing</b>	<b>mm</b> <b>3625</b>	
		vii)	Partial discharge of bushings at Ur (line end and neutral)	<b>pC</b> <b>&lt; 10</b>	

Sl. No.	Existing Clause	New / Revised Clause					
<p>....</p> <p><b>Neutral Grounding Reactor (NGR) and Surge Arrester for 400kV Line Reactors (as applicable)</b></p>		23.	Maximum partial discharge level at $1.58U_r/\sqrt{3}$	pC	100		
		24.	Vibration and tank stress at rated voltage		Max $\leq 200$ microns peak to peak Average $\leq 60$ microns peak to peak Tank stress: $\leq 2.0$ kg/sq.mm at any point of tank		
		25.	Maximum noise pressure level at rated voltage & frequency	dB	80		
		26.	Maximum Permissible load Losses at rated Voltage, Frequency and at 75° C		Total loss	I <sup>2</sup> R Loss	
		i)	125MVA <sub>r</sub> 420kV	kW	160	90	
		27.	Insulating Oil		<u>Unused</u> inhibited or <u>uninhibited transformer oil</u> , conforming to IEC-60296-2012		
		<p>....</p> <p><b>Neutral Grounding Reactor (NGR) and Surge Arrester for 400kV Line Reactors (as applicable)</b></p>		<p>....</p> <p><b>Neutral Grounding Reactor (NGR) and Surge Arrester for 400kV Line Reactors</b></p> <p><b><u>TSP shall provide NGR of suitable value (Ohm) as per actual line length. NGR shall be oil filled or dry type air core for outdoor application. Line and ground side of NGR shall be rated for 145kV</u></b></p>			

Sl. No.	Existing Clause	New / Revised Clause
	<p><u>The neutral grounding reactors are required for grounding of the neutral point of shunt reactors to limit the secondary arc current and the recovery voltage to a minimum value. NGR shall be oil filled type suitable for outdoor application. Line and ground side of NGR shall be rated for 145kV and 36kV class of insulation respectively. NGR shall be rated for continuous current of 10A and short time current of 60A r.m.s for 10 seconds. It shall be solidly connected between neutral of shunt reactor and earth.</u></p> <p><u>The surge arresters (rated voltage 120kV) shall be of heavy duty station class type. It shall be physically located between the neutral of shunt reactor (brought out at 145kV class bushing) and neutral grounding reactor. The surge arresters shall conform in general to IEC-60099-4. Surge arresters shall be of gapless type without any series or shunt gap. Arresters shall be hermetically sealed units, of self-supporting construction, suitable for mounting on structures.</u></p> <p><b>2.3. Circuit Breakers (AIS)</b></p> <p>The circuit breakers and accessories shall conform to IEC: 62271-100, IEC: 62271-1 and shall be of SF6 Type. The rated break time shall not exceed 40 ms for 400kV circuit breakers and 60 ms for 220kV circuit breakers. 400kV and 220kV Circuit breakers shall be provided with single phase and three phase auto reclosing. The Circuit breakers controlling 400kV lines of more than 200km length shall be provided with pre insertion closing resistor of about 400 ohms maximum with 8 ms minimum insertion time or Controlled Switching Device. The short line fault capacity shall be same as the rated capacity and this is proposed to be achieved without use of opening resistors. The</p>	<p><u>and 36kV class of insulation respectively. Oil filled NGR shall be rated for continuous current of 10A and short time current of 60A r.m.s for 10 seconds while air core NGR shall be rated for continuous current of 20A and short time current of 240A r.m.s for 1 minute. However, the air core NGR shall be designed for a short time current of 600 Amp r.m.s to ensure mechanical robustness. It shall be solidly connected between neutral of shunt reactor and earth. The air core NGR shall be mounted on support structure (non-magnetic material) high above ground level (2.55 meter) to allow free and safe access at ground level for personnel.</u></p> <p><u>The surge arresters (rated voltage 120kV) shall be provided &amp; physically located between the neutral of shunt reactor (brought out at 145kV class bushing) and neutral grounding reactor. The surge arresters shall be of heavy duty station class gapless Metal oxide (ZnO) type, conforming in general to IEC-60099-4. Arresters shall be hermetically sealed units, of self-supporting construction, suitable for mounting on structures.</u></p> <p><b>2.3. Circuit Breakers (AIS)</b></p> <p>The circuit breakers and accessories shall conform to IEC: 62271-100, IEC: 62271-1 and shall be of SF6 Type. <u>The circuit breakers shall be of class C2-M2 (as per IEC) with regard to restrike probability during capacitive current breaking and mechanical endurance.</u> The rated break time shall not exceed 40 ms for 400kV circuit breakers and 60 ms for 220kV circuit breakers. 400kV and 220kV Circuit breakers shall be provided with single phase and three phase auto reclosing. The Circuit breakers controlling 400kV lines of more than 200km length shall be provided with pre insertion closing resistor of about 400 ohms maximum with 8 ms minimum insertion time or Controlled Switching</p>

Sl. No.	Existing Clause	New / Revised Clause
	<p>controlled switching device shall be provided in 400kV Circuit breaker of switchable line reactor bay and in Main &amp; Tie bay circuit breakers of line with non-switchable line reactors, Bus reactors <b><u>and 765/400kV Transformers (whenever applicable).</u></b></p> <p><b>2.4. Isolators (AIS)</b></p> <p>The isolators shall comply to IEC 62271-102 in general. 400 kV and 220kV Isolators shall be double break type. All Isolators and earth switches shall be motor operated. Earth switches shall be provided at various locations to facilitate maintenance. Isolator rated for 400kV and 220kV shall be of extended mechanical endurance class-M2 <b><u>and all earth switches shall be class M0 as per IEC-622/1-102.</u></b> Main blades and earth blades shall be interlocked and interlock shall be fail safe type. 400kV and 220kV earth switch for line isolator shall be suitable for induced current switching duty as defined for Class- B.</p> <p><b>2.5. Current Transformers (AIS)</b></p> <p>Current Transformers shall comply with IEC 61869 in general. All ratios shall be obtained by secondary taps only. Generally, Current Transformers (CT) for 400kV shall have six cores (four for protection and two for metering). 220kV Current Transformers shall have five cores (four for protection and one for metering). The burden and knee point voltage shall be in accordance with the requirements of the system including possible feeds for telemetry. Accuracy class for protection core shall be PX and for metering core it shall be 0.2S. The rated burden of cores shall be closer to the maximum burden requirement of metering &amp; protection system for better sensitivity and accuracy.</p>	<p>Device. The short line fault capacity shall be same as the rated capacity and this is proposed to be achieved without use of opening resistors. The controlled switching device shall be provided in 400kV_Circuit breaker of switchable line reactor bay and in Main &amp; Tie bay <b><u>400 kV</u></b> circuit breakers of line with non-switchable line reactors, and Bus reactors.</p> <p><b>2.4. Isolators (AIS)</b></p> <p>The isolators shall comply to IEC 62271-102 in general. 400 kV and 220kV Isolators shall be double break type. All Isolators and earth switches shall be motor operated. Earth switches shall be provided at various locations to facilitate maintenance. Isolator rated for 400kV and 220kV shall be of extended mechanical endurance class-M2 and <b><u>suitable for bus transfer current switching duty.</u></b> Main blades and earth blades shall be interlocked and interlock shall be fail safe type. 400kV and 220kV earth switch for line isolator shall be suitable for induced current switching duty as defined for Class- B.</p> <p><b>2.5. Current Transformers (AIS)</b></p> <p>Current Transformers shall comply with IEC 61869 in general. All ratios shall be obtained by secondary taps only. Generally, Current Transformers (CT) for 400kV shall have six cores (four for protection and two for metering). 220kV Current Transformers shall have five cores (four for protection and one for metering). The burden and knee point voltage shall be in accordance with the requirements of the system including possible feeds for telemetry. Accuracy class for protection core shall be PX and for metering core it shall be 0.2S. The rated burden of cores shall be closer to the maximum burden requirement of metering &amp;</p>

Sl. No.	Existing Clause	New / Revised Clause
	<p><b>2.6. Capacitor Voltage Transformers (AIS)</b></p> <p>Capacitive Voltage transformers shall comply to IEC 61869 in general. These shall have three secondaries out of which two shall be used for protection and one for metering. Accuracy class for protection cores shall be 3P and for metering core it shall be 0.2. The Capacitive voltage transformers on lines shall be suitable for Carrier Coupling. The Capacitance of CVT for 400kV and 220kV shall be of 4400/8800 pF depending on PLCC requirements. The rated burden of cores shall be closer to the maximum burden requirement of metering &amp; protection system for better sensitivity and accuracy.</p> <p><b>2.7. Surge Arresters (AIS)</b></p> <p>336kV &amp; 216kV Station class, <b>current limiting</b>, heavy duty gapless type Surge arresters conforming to IEC 60099-4 in general shall be provided for 420kV &amp; 245kV systems respectively. The rated voltage of Surge arrester and other characteristics are chosen in accordance with system requirements. Surge arresters shall be provided near line entrances, transformers &amp; Reactor so as to achieve proper insulation coordination. Surge Arresters shall be provided with porcelain/ polymer housing fitted with pressure relief devices. A leakage current monitor with surge counter shall be provided with each surge arrester.</p> <p><b>2.8. Projection Relaying &amp; Control System</b></p>	<p>protection system <b>(not more than 20VA for metering core)</b> for better sensitivity and accuracy. <b>The Instrument security factor shall be less than 5.</b></p> <p><b>2.6. Capacitor Voltage Transformers (AIS)</b></p> <p>Capacitive Voltage transformers shall comply to IEC 61869 in general. These shall have three secondaries out of which two shall be used for protection and one for metering. Accuracy class for protection cores shall be 3P and for metering core it shall be 0.2. The Capacitive voltage transformers on lines shall be suitable for Carrier Coupling. The Capacitance of CVT for 400kV and 220kV shall be of 4400/8800 pF depending on PLCC requirements. The rated burden of cores shall be closer to the maximum burden requirement of metering &amp; protection system <b>(not more than 50VA for metering core)</b> for better sensitivity and accuracy.</p> <p><b>2.7. Surge Arresters (AIS)</b></p> <p>336kV &amp; 216kV Station class, heavy duty gapless type Surge arresters conforming to IEC 60099-4 in general shall be provided for 420kV &amp; 245kV systems respectively. The rated voltage of Surge arrester and other characteristics are chosen in accordance with system requirements. Surge arresters shall be provided near line entrances, transformers &amp; Reactor so as to achieve proper insulation coordination. Surge Arresters shall be provided with porcelain/ polymer housing fitted with pressure relief devices. A leakage current monitor with surge counter shall be provided with each surge arrester.</p> <p><b>2.8. Projection Relaying &amp; Control System</b></p>

Sl. No.	Existing Clause	New / Revised Clause
	<p>The protective relaying system proposed to be provided for transmission lines, auto-transformers, reactors and bus bars to minimize the damage to the equipment in the events of faults and abnormal conditions, is dealt in this section. All main protective relays shall be numerical type with IEC 61850 communication interface. All numerical relays shall have built in disturbance recording feature.</p> <p>.....</p> <p><b>a) Transmission Lines Protection</b>  400kV and 220kV lines shall have Main-I numerical three zone distance protection scheme with carrier aided inter-tripping feature. 400kV and 220kV lines shall also have Main-II numerical distance protection scheme like Main-I but from different make that of Main-I. The Main-I and Main-II protection relays of same make may be provided only if they are of different hardware <b><u>&amp; manufacturing platform.</u></b></p> <p>....</p> <p>Line Current Differential relay (with back up distance protection feature) as Main-I and Main-II shall be considered at both ends for short lines (line length below 30kM) having Fibre Optic communication link. Differential relay at remote end shall be provided by the TSP. Associated power &amp; control cabling and</p>	<p>The protective relaying system proposed to be provided for transmission lines, auto-transformers, reactors and bus bars to minimize the damage to the equipment in the events of faults and abnormal conditions, is dealt in this section. All main protective relays shall be numerical type with IEC 61850 communication interface. All numerical relays shall have built in disturbance recording feature.</p> <p><b><u>The protection circuits and relays of transformer and reactor shall be electrically and physically segregated into two groups each being independent and capable of providing uninterrupted protection even in the event of one of the protection groups failing, to obtain redundancy, and to take protection systems out for maintenance while the equipment remains in service.</u></b></p> <p>.....</p> <p><b>a) Transmission Lines Protection</b>  400kV and 220kV lines shall have Main-I numerical three zone distance protection scheme with carrier aided inter-tripping feature. 400kV and 220kV lines shall also have Main-II numerical distance protection scheme like Main-I but from different make that of Main-I. The Main-I and Main-II protection relays of same make may be provided only if they are of different hardware, <b><u>manufacturing platform or different principle of operation.</u></b></p> <p>....</p> <p><b><u>However,</u></b> Line Current Differential relay (with back up distance protection feature) as Main-I and Main-II shall be considered at both ends for short lines (line length below 30kM) having Fibre Optic communication link. Differential relay at remote end shall be provided by the TSP. Associated power &amp; control cabling and</p>

Sl. No.	Existing Clause	New / Revised Clause
	<p>integration with SAS at remote end shall be provided by respective bay owner.</p> <p>....</p> <p><b>b) Auto Transformer Protection</b></p> <p>.....</p> <p>Suitable monitoring, control (operation of associated circuit breaker &amp; isolator) and protection for LT auxiliary transformer connected to tertiary winding of auto-transformer for the purpose of auxiliary supply shall be provided. The Over current <b><u>and open delta protection is required</u></b> to be provided for the auxiliary transformer. These protection and control may be provided as built in feature either in the bay controller to be provided for the auxiliary system or in the control &amp; protection IEDs to be provided for autotransformer.</p> <p>....</p> <p><b>2.9. Substation Automation System</b></p> <p>a) ....</p> <p>The functions of control, annunciation, disturbance recording, event logging and measurement of electrical parameters shall be integrated in Substation Automation System.</p> <p><b><u>The Automation System shall be provided with the facility of communication and control for remote end operation so that by providing remote HMI and suitable communication link, the substation can be controlled from a remote location. Mode of communication shall be considered as optical fibre or leased line based on IEC-60870-5-104 communication protocol.</u></b></p>	<p>integration with SAS at remote end shall be provided by respective bay owner.</p> <p>....</p> <p><b>b) Auto Transformer Protection</b></p> <p>.....</p> <p>Suitable monitoring, control (operation of associated circuit breaker &amp; isolator) and protection for LT auxiliary transformer connected to tertiary winding of auto-transformer for the purpose of auxiliary supply shall be provided. The Over current <b><u>and other necessary protection shall be provided</u></b> for the auxiliary transformer. These protection and control may be provided as built in feature either in the bay controller to be provided for the auxiliary system or in the control &amp; protection IEDs to be provided for autotransformer.</p> <p>.....</p> <p><b>2.9. Substation Automation System</b></p> <p>a) ...</p> <p>The functions of control, annunciation, disturbance recording, event logging and measurement of electrical parameters shall be integrated in Substation Automation System.</p>

Sl. No.	Existing Clause	New / Revised Clause
	<p>At new substations, the Substation Automation System (SAS) shall be suitable for operation and monitoring of the complete substation including proposed future bays/elements.</p> <p>...</p>	<p>At new substations, the Substation Automation System (SAS) shall be suitable for operation and monitoring of the complete substation including proposed future bays/elements.</p> <p>...</p>
3.	<p><b>3.1. AC &amp; DC power supplies</b></p> <p>For catering the requirements of three phase &amp; single phase AC supply and DC supply for various substation equipment, the following arrangement is envisaged:-</p> <p>i) .....</p> <p>Additionally, Active Energy Meters may be provided at the same point in the 33kV tertiary of Transformer by local SEB/DISCOM for energy</p> <p>.....</p> <p><b>iii) Suitable AC &amp; DC distribution boards and associated LT Switchgear shall be provided at new substation. <u>For new substation, following switch boards with minimum rating as specified here under shall be considered with duplicate supply:</u></b></p> <p>(a) 415V Main Switch board – <b>2</b> nos.  (b) AC distribution board – <b>2</b> nos.  (c) ....  (f) 48 Volt DC distribution board – 2 nos.</p> <p><b><u>Sizing of LT Switchgear shall be suitable to cater the requirement for all present and future bays. AC &amp; DC</u></b></p>	<p><b>3.1. AC &amp; DC power supplies</b></p> <p>For catering the requirements of three phase &amp; single phase AC supply and DC supply for various substation equipment, the following arrangement is envisaged:-</p> <p>i) .....</p> <p>Additionally, Active Energy Meters may be provided at the same point in the 33kV tertiary of Transformer by local SEB/DISCOM for energy <b>accounting</b></p> <p>.....</p> <p><b>iii) Suitable AC &amp; DC distribution boards and associated LT Switchgear shall be provided at new substation. <u>Sizing of LT Switchgear shall be suitable to cater the requirement for all present and future bays. AC &amp; DC distribution boards shall have modules for all the present and future feeders as specified.</u></b></p> <p><b><u>For new substation, following switch boards shall be considered with duplicate supply with bus coupler/ sectionalizer and duplicate outgoing feeders except for Emergency lighting distribution board which shall have only one incoming feeder:</u></b></p> <p>(a) 415V Main Switch board – <b>1</b> no.  (b) AC distribution board – <b>1</b> no.  (c) ....</p>

Sl. No.	Existing Clause	New / Revised Clause
	<p><b><u>distribution boards shall have modules for all the feeders (including future as specified).</u></b></p> <p><b>3.2. Fire Fighting System</b></p> <p>....</p> <p>Further, adequate water hydrants and portable fire extinguishers shall be provided in the substations. The main header of firefighting system shall be suitable for extension to bays covered under the future scope; necessary piping interface in this regard shall be provided.</p> <p><b><u>Beam type heat detection for GIS hall fire protection system shall be provided for all the GIS halls.</u></b></p> <p>....</p> <p><b>3.7. Visual monitoring system for watch and ward of substation premises:</b></p> <p><b><u>Visual monitoring system for effective watch and ward of substation premises covering the areas of entire switchyard, Control room building, other buildings/stores and main gate, shall be provided. The Visual Monitoring System shall have provision of WAN connectivity for remote monitoring.</u></b></p> <p><b><u>The number of cameras and their locations shall be decided in such a way that any location covered in the substation area can be scanned. The cameras shall be located in such a way to monitor at least:</u></b></p>	<p>(f) 48 volt DC distribution board – 2 nos.</p> <p><b>3.2. Fire Fighting System</b></p> <p>.....</p> <p>Further, adequate water hydrants and portable fire extinguishers shall be provided in the substations. The main header of firefighting system shall be suitable for extension to bays covered under the future scope; necessary piping interface in this regard shall be provided.</p> <p>.....</p> <p><b>3.7. Visual monitoring system for watch and ward of substation premises:</b></p> <p><b><u>Visual monitoring system for effective watch and ward of substation premises shall cover all the transformers and reactors, all other major AIS Equipment (such as CB, isolators, CT, CVT,SA etc. as applicable). GIS bays, panel room, all the gates of switchyard and all entry and exit points of control room building and accordingly the location of cameras shall be decided. The camera shall be high definition color CCD camera with night vision feature. The VMS data partly/completely shall be recorded (minimum for 15 days) at least @25fps (or better) and stored on network video recorder. The system shall use video signals from various cameras installed at different locations, process them for viewing on workstations/monitors in the control room and simultaneously record all the cameras. Mouse/keyboard controllers shall be used</u></b></p>

Sl. No.	Existing Clause	New / Revised Clause
	<p>1. <u>The operation of each and every isolator pole of the complete yard in case of AIS Substation.</u></p> <p>2. <u>The Operation of each bay bays of GIS Hall as applicable.</u></p> <p>3. <u>All the Transformer and Reactors, all the Entrance doors of Control Room Building, GIS hall and any other building as applicable.</u></p> <p>4. <u>All the gates of switchyard.</u></p> <p>5. <u>Main entrance Gate</u></p> <p>6. <u>All other major AIS Equipment (such as CB, CT, CVT, SA etc. as applicable)</u></p> <p>At existing substations, the visual monitoring system <u>as</u> available shall be augmented as required.</p>	<p><u>for pan, tilt, zoom and other functions of the desired camera. The Visual Monitoring System shall have provision of WAN connectivity for remote monitoring.</u></p> <p><u>All camera recordings shall have Camera ID &amp; location/area of recording as well as date/time stamp. The equipment should generally conform to Electromagnetic compatibility requirement for outdoor equipment in EHV substation.</u></p> <p>At existing substations, the visual monitoring system <u>if</u> available shall be augmented as per <u>existing or better specification</u> as required.</p>
4.	<p><b>4.0. General Facilities</b></p> <p>....</p> <p>e) In 400kV switchyard, if spare bay of half diameter is identified as future, all the equipment for Tie &amp; Future bay shall be designed considering the current rating of line bay i.e. <b>3000A.</b></p>	<p><b>4.0. General Facilities</b></p> <p>...</p> <p>e) In 400kV switchyard, if spare bay of half diameter is identified as future, all the equipment for Tie &amp; Future bay shall be designed considering the current rating of line bay i.e. <b>3150A.</b></p>
5.	<p><b><u>PLCC</u></b></p> <p><b><u>PLCC &amp; PBAX: Power line carrier communication (PLCC) equipment complete for speech, teleprotection commands and data channels shall be provided on each transmission line. The protections for transmission line and the line compensating equipment shall have hundred percent back up communication channels i.e. two channels for tele- protection in addition to one channel for speech plus data for each direction.. The PLCC equipment shall in brief include the following:-</u></b></p>	<p><b>Deleted.</b></p>

Sl. No.	Existing Clause	New / Revised Clause
	<p><u>Coupling device, line traps, carrier terminals, protection couplers, HF cables, PABX (if applicable) and maintenance and testing instruments.</u></p> <p><u>A telephone exchange (PABX) of 24 lines shall be provided at new substations as means of effective communication among various buildings of the substation, remote end substations and with control centers (RLDC/SLDC) etc.</u></p> <p><u>Coupling devices shall be suitable for phase to phase coupling for 765kV &amp; 400kV Transmission lines. The pass band of coupling devices shall have sufficient margin for adding communication channel in future if required. Necessary protection devices for safety of personnel and low voltage part against power frequency voltages and transient over voltage shall also be provided.</u></p> <p><u>The line traps shall be broad band tuned suitable for blocking the complete range of carrier frequencies. Line Trap shall have necessary protective devices such as lightning arresters for the protection of tuning device. Decoupling network consisting of line traps and coupling capacitors may also be required at certain substation in case of extreme frequency congestion.</u></p> <p><u>The carrier terminals shall be of single side-band (SSB) amplitude modulation (AM) type and shall have 4 kHz band width. PLCC Carrier terminals and Protection couplers shall be considered for both ends of the line.</u></p> <p><u>PLCC equipment for all the transmission lines covered under the scheme (consisting of one set of analog PLCC channel along with circuit protection coupler and one set of Digital protection coupler for both ends) shall be provided by TSP. Further, PLCC equipment for both ends of transmission lines not covered under present scope</u></p>	

Sl. No.	Existing Clause	New / Revised Clause
	<p><b><u>shall be provided by developer of lines. However, CVT &amp; Wave trap for all the line bays under present scope shall be provided by TSP.</u></b></p> <p><b><u>TSP shall provide/undertake necessary addition/modification/shifting/re-commissioning etc. of PLCC equipment due to LILO of transmission lines (wherever applicable).</u></b></p> <p><b><u>All other associated equipment like cabling, coupling device and HF cable shall also be provided by the TSP. The wave trap and CVT required for PLCC at remote end shall be provided by respective bay owner.</u></b></p>	
6.	<p><b>SPECIFIC TECHNICAL REQUIREMENTS FOR COMMUNICATION</b></p> <ul style="list-style-type: none"> <li>• <b>Ramgarh-II PS – Fatehgarh- II PS 400kV D/c line (Twin HTLS)</b></li> </ul> <p>On Ramgarh-II PS – Fatehgarh- II PS 400kV D/c line one OPGW containing 24 Fibres is to be installed by the TSP in place of conventional earth wire during the construction of line. The installation of OPGW shall be done from gantry of Ramgarh-II PS up to gantry of – Fatehgarh- II PS and shall be terminated in a Joint Box to be provided by TSP at both the ends. In case of requirement of repeater to establish link between Ramgarh–II PS – Fatehgarh-II PS , the OPGW (48F) connectivity from power line crossing point upto repeater station shall also be in the scope of TSP.</p>	<p><b>SPECIFIC TECHNICAL REQUIREMENTS FOR COMMUNICATION</b></p> <ul style="list-style-type: none"> <li>• <b>Ramgarh-II PS – Fatehgarh- II PS 400kV D/c line (Twin HTLS)</b></li> </ul> <p><b><u>OPGW:</u></b></p> <p>On Ramgarh-II PS – Fatehgarh- II PS 400kV D/c line <b><u>under present scope</u></b> one OPGW containing 24 Fibres is to be installed by the TSP in place of conventional earth wire during the construction of line. The installation of OPGW shall be done from gantry of Ramgarh-II PS up to gantry of – Fatehgarh- II PS and shall be terminated in a Joint Box to be provided by TSP at both the ends. In case of requirement of repeater to establish link between Ramgarh–II PS – Fatehgarh-II PS , the OPGW (48F) connectivity from power line crossing point upto repeater station shall also be in the scope of TSP.</p> <p><b><u>The protection system for 400kV and higher voltage transmission line and the line compensating equipment shall have one hundred percent back up communication channels i.e.</u></b></p>

Sl. No.	Existing Clause	New / Revised Clause
	<ul style="list-style-type: none"> <li>• <b><u>Ramgarh-II PS- Jaisalmer-II (RVPN) 400 kV D/c line (Twin HTLS)</u></b></li> </ul> <p>On Ramgarh-II PS – Jaisalmer-II (RVPN) 400kV D/c line one OPGW containing 24 Fibres is to be installed by the TSP in place of conventional earth wire during the construction of line. The installation of OPGW shall be done from gantry of Ramgarh-II PS up to gantry of Jaisalmer-II (RVPN) and shall be terminated in a Joint Box to be provided by TSP at both the ends. In case of requirement of repeater to establish link between Ramgarh-II PS – Jaisalmer-II (RVPN), the OPGW (48F) connectivity from power line crossing point upto repeater station shall also be in the scope of TSP.</p> <p>.....</p>	<p><b><u>two channels for tele- protection in addition to one channel for speech plus data for each direction.</u></b></p> <ul style="list-style-type: none"> <li>• <b><u>Ramgarh-II PS- Jaisalmer-II (RVPN) 400 kV D/c line (Twin HTLS)</u></b></li> </ul> <p><b><u>OPGW:</u></b></p> <p>On Ramgarh-II PS – Jaisalmer-II (RVPN) 400kV D/c line <b><u>under present scope</u></b> one OPGW containing 24 Fibres is to be installed by the TSP in place of conventional earth wire during the construction of line. The installation of OPGW shall be done from gantry of Ramgarh-II PS up to gantry of Jaisalmer-II (RVPN) and shall be terminated in a Joint Box to be provided by TSP at both the ends. In case of requirement of repeater to establish link between Ramgarh-II PS – Jaisalmer-II (RVPN), the OPGW (48F) connectivity from power line crossing point upto repeater station shall also be in the scope of TSP.</p> <p><b><u>The protection system for 400kV and higher voltage transmission line and the line compensating equipment shall have one hundred percent back up communication channels i.e. two channels for tele- protection in addition to one channel for speech plus data for each direction.</u></b></p> <p>.....</p> <p><b><u>PLCC &amp; PBAX:</u></b></p> <p><b><u>Power line carrier communication (PLCC) equipment complete for speech, teleprotection commands and data channels shall be provided on each transmission line. The protections for</u></b></p>

Sl. No.	Existing Clause	New / Revised Clause
		<p><u>transmission line and the line compensating equipment shall have hundred percent back up communication channels i.e. two channels for tele- protection in addition to one channel for speech plus data for each direction. The PLCC equipment shall in brief include the following:-</u></p> <ul style="list-style-type: none"> <li>• <u>Coupling device, line traps, carrier terminals, protection couplers, HF cables, PABX (if applicable) and maintenance and testing instruments.</u></li> <li>• <u>At new substation, a telephone exchange (PABX) of 24 lines shall be provided at as means of effective communication among various buildings of the substation, remote end substations and with control centers (RLDC/SLDC) etc.</u></li> <li>• <u>Coupling devices shall be suitable for phase to phase coupling for 765kV &amp; 400kV Transmission lines. The pass band of coupling devices shall have sufficient margin for adding communication channel in future if required. Necessary protection devices for safety of personnel and low voltage part against power frequency voltages and transient over voltage shall also be provided.</u></li> <li>• <u>The line traps shall be broad band tuned suitable for blocking the complete range of carrier frequencies. Line Trap shall have necessary protective devices such as lightning arresters for the protection of tuning device. Decoupling network consisting of line traps and coupling capacitors may also be required at certain substation in case of extreme frequency congestion.</u></li> </ul>

Sl. No.	Existing Clause	New / Revised Clause
		<ul style="list-style-type: none"> <li>• <u>The carrier terminals shall be of single side-band (SSB) amplitude modulation (AM) type and shall have 4 kHz band width. PLCC Carrier terminals and Protection couplers shall be considered for both ends of the line.</u></li> <li>• <u>PLCC equipment for all the transmission lines covered under the scheme (consisting of one set of analog PLCC channel along with circuit protection coupler and one set of Digital protection coupler for both ends) shall be provided by TSP. CVT &amp; Wave trap for all line bays, under present scope shall be provided by TSP.</u></li> <li>• <u>TSP shall provide/undertake necessary addition/modification/shifting/re-commissioning etc. of PLCC equipment due to LILO of transmission lines (wherever applicable).</u></li> <li>• <u>All other associated equipment like cabling, coupling device and HF cable shall also be provided by the TSP.</u></li> </ul>